

Public Address Combination Amplifier FCVC3000

Overview

- 250Watt, 2Ways, 24-Zone Digital Amplifier
- 24 Output select switch & Group select key, Simultaneous broadcast
- FM Tuner, 1CDP(MP3+WMA) installed
- Mic. for Emergency broadcasting installed
- PC remote control and Program broadcasting through RS-232C
- Priority : EM > Fire > Tel In > Remote Mic > Mic 1 > Mic 2~6 > Siren > Chime > Ringer



Description

ELECTRICAL

*0dB=0.775Vrms

- Input Sensitivity
 - Mic Input 1~6(Balance) -50dB ±3dB
 - Aux Input 1~2(Unbalance) -10dB ±3dB
 - Aux Input 3(Unbalance) +4dB ±3dB
 - Remote Mic Station Input 1~4(Balance) 0dB ±3dB
- T. H. D Less than 1%
- S/N More than 90dB
- Output Power 250W/2CH
- Pre Out & Rec Out Sensitivity
 - Pre Out(Balance) 0dB ±3dB
 - Rre Out(Unbalance) 0dB ±3dB

GENERAL

- Power Source 100~120VAC or 220~240VAC; 50/60Hz, 24VDC (supplied AC mains transformer depends on local requirements)
- Weight 22kg/48.5lb
- Dimensions 482(W)x177(H)x369(D)mm
19(W)x6.9(H)x14.5(D)in

ADEVA LTD. Fire Alarm Systems

Guldeste Sok. No:24 Yakacik
Kartal / Istanbul / Turkey

Tel: +90 (0)216 5982800 Fax: +90 (0)216 5982899
Email: info@adevafire.com www.adevafire.com

Copyright © 2009 ADEVA. All rights reserved.

All technical data is correct at time of publication and is subject to change without notice. All trademarks acknowledged. Installation information: in order to ensure full functionality, refer to the installation instructions as supplied.